

§Small-sized plug-in transducer§

INSTALLATION BASE

Application

A multiple unit installation base which can house 1-output/2-output type small-sized transducers in a lot. Because the base is collective power source type, it can reduce wiring of power source. Please use the base when installing multiple transducers.



480×130×120mm/1.6kg

Note: installation base is shipped without transducers.

Feature

1. There are two types, storable quantity 16 units and 8 units. Choose a storable quantity 8-unit type if there are few transducers (1-output or 2-output) to install, or when storage space is limited.
2. Two types, wall mounting and DIN rail mounting are available.
3. A terminal block or a connector can be chosen as the 1st output in accordance with output destination.

Specification

How to specify

Type name

Specification code

FWBS - [] [] [] []

- [] []

Storable quantity	Way of mounting	Individual power switch	Output pattern of the 1 st output	Output pattern of the 2 nd output
<div style="border: 1px solid black; padding: 2px;">16</div> : 16 units <div style="border: 1px solid black; padding: 2px;">08</div> : 8 units	<div style="border: 1px solid black; padding: 2px;">W</div> : Wall mounting <div style="border: 1px solid black; padding: 2px;">D</div> : DIN rail mounting	<div style="border: 1px solid black; padding: 2px;">N</div> : No switch	<div style="border: 1px solid black; padding: 2px;">0</div> : Terminal block <div style="border: 1px solid black; padding: 2px;">1</div> : Connector <small>(FCN-364P040-AU made by Fujitsu)</small>	<div style="border: 1px solid black; padding: 2px;">0</div> : Terminal block

Note: If transducers of different withstand voltage were installed in a case, and a withstand voltage test was implemented, transducers may be damaged by test voltage. Input/output withstand voltage test of small-sized transducers and installation base should be carried out individually or carry out voltage test of devices of the same strength with test voltage that all devices can bear.

Terminal block

Specifications	Power source (earth)	Input	Output (terminal block output)
Terminal screw	M3.5×8L (with washer)	M3.5×7L (with washer)	M3.5×7L (with washer)
Matching cable	2mm ²	2mm ²	2mm ²
Matching crimping terminal	1.25-3.6 2-3.5 1.25-4 2-4 1.25-5	1.25-3.5 2-3.5	1.25-3.5 2-3.5

*Name of crimping terminal

1.25

 -

3.5

Nominal diameter of screw used

Section area of nominal strand wire mm²